mont-bell 取扱説明書

Emergency Robe

この度はお買いあげいただき、誠にありがとうございます。この取扱説明書(以下「本説明書」といいます)は本製品の 正しい取扱方法を説明しています。ご使用の前に本説明書をよくお読みいただき、正しい使用方法をご確認ください。 ただし、本説明書は本製品の基本的な使用方法を示すものです。安全な条件のもとで十分な練習を行い、正しい使用 方法を習得してください。なお、ご不明な点等ございましたら、販売店もしくは(株) モンベル カスタマー・サービスまで お問い合わせください。本説明書は大切に保管してください。

■ 安全上の注意 ぶずお読みください

巻悠土 場合により人が死亡または重傷を負う可能性が想定される内容です。 **四** 軽傷または物的損害が発生する頻度が高いことが想定される内容です。

- ○救助者及び遭難者ともにロープを身体に結びつけたり、立木などに固定することは絶対しないでください。 素早くロープを手放せないと二次災害を招く恐れがあります。
- ○クライミングや懸垂下降を目的としたご使用は絶対にしないでください。

注意 人が傷害を負ったり物的損害の発生が想定される内容です。

- ○本製品の改造や分解などは絶対にしないでください。性能が損なわれ、充分な強度が発揮できない恐れがあります。
- ○使用前は毎回必ず点検をしてください。老朽化が認められる場合や損傷が認められたり、疑わしい場合は 直ちに本製品の使用を中止してください。本来の性能が発揮できない恐れがあります。
- ○正しいお手入れ方法、保管方法を守ってください。誤ったお手入れや保管方法を行うと、本来の性能を発 揮できない恐れがあります。
- ○ロープに大きな傷や結び目に緩みがないかもチェックしてください。ロープが古くなったり、高い強度がかか った場合はご使用を取りやめ、新しい製品をお買い求めください。

巻き結び

インク・ノット

物をしっかりと縛る時の結び

■ 使用方法

- ○ロープ本来の強度を発揮させるために、結び目をゆるみがない様にしっかり締めてください。
- ○ロープの末端は結び目から最低 3cm 以上とってください。

もやい結び

ボーライン・ノット


ロープを人や物などに結ぶ時

- ○ロープの端に輪を作る結び方

○結びやすく、緩みにくい。

○避難生活時に幅広い用途に使用する。 ○同じ太さ、材質のロープ同士を継ぎ ○輪の大きさが変化せず、強度が高い。 ○結びやすく、解きやすい。







本結び

リーフ・ノット

同じ太さのロープを繋ぐ結び

○簡単に結べ、素早く解くことができる。

足す時に使用する。

ダブル・フィッシャーマンズ・ノット

物をしっかりと縛る時の結び


- ○結び方が複雑で、解けにくい。


8字結び

フィギュア・オブ・エイト・ノット

同じ太さのロープを繋ぐ結び

- ○止め結びより大きいコブを作れる。
- ○比較的解きやすい。





■ お手入れ方法

間違ったお手入れ方法や保管方法は本製品の寿命を縮めます。使用後や保管時は以下の点を参考にしてください。

- ○ご使用後は真水ですすいで、砂や汚れを洗い流してから風诵りの良い場所で陰干しをしてください。
- ○汚れがひどい場合はぬるま湯と洗剤で洗ってください。その場合はすすぎを十分に行い、洗剤が残らない ようにしてください。

■ 保管方法

- ○直射日光の当たらない風通しの良い場所を選んでください。
- ○本製品を火のそばや暖房器具のそばなどの高温になる所に置かないでください。変形や損傷の原因になります。

■ 廃棄方法

○廃棄方法はお住まいの自治体の収集方法に従ってください。

■ アフターサービス

お買い求めいただきました本製品は万全を期して製造しておりますが、万一不備な点がございましたら、お買 い求めいただいた販売店、もしくは下記の弊社窓口までご連絡ください。

製造上の欠陥による不具合の場合は無償で交換させていただきます。なお、修理、交換等の要否につきまし ては、弊社の裁量にて判断させていただきます。

なお、以下のような原因での破損、不良につきましては保証いたしませんのでご了承ください。

- ○本製品の誤った使用方法によるもの
- ○間違ったお手入れ、保管方法、経年変化による素材劣化
- ○乱暴な取り扱いによるもの
- ○その他、製造上の欠陥以外の原因によるもの

破損時は弊社にて診断をして、修理が可能な場合はご要望により有僧にて修理させていただきます。

■ 仕様

品 名:防災用ロープ

サ イ ズ:Φ6mm

伸 75 率:5.8%

さ:7m

破断強度: 880kgf (静的荷重時)

量:27g/m

MADE IN USA

■ その他

本製品の仕様、デザインは予告なく変更されることがあります。また、重量などのスペックには誤差が生じる場合があります。

株式会社 モンペル 本 社 〒550-0013 大阪市西区新町2-2-2 Tel. 06-6531-3544 フリーコール: @ 0088-22-0031 商品についてのお問い合わせはカスタマー・サービスまで

44-2761-1802

User's Manual

Emergency Rope

Emergency Rope

Thank you for purchasing this product. Before using, please carefully read this manual for instructions on the proper care and usage of this product.

Please understand this manual only explains how to use the product and does not go into detail regarding using the product safely. You are personally responsible for learning the proper techniques and safety procedures for using this equipment.

If you have any questions regarding this product, please contact Montbell Customer Service or the store of original purchase. Keep this manual for future reference.

■ Safety Warnings! Please read carefully.



Under certain conditions, use of this product can result in injury, death, or property damage.

- ODO NOT wrap the rope around the body of the rescuer or rescuee, or rooted trees. In case of an emergency, it may be necessary to release the rope guickly.
- ODo NOT use for climbing or for rapelling.

CAUTION!

Under certain conditions, use of this product can result in injury or property damage.

- OD NOT modify or alter this product. Improper modifications and alterations can damage the product and impair functionality.
- OPrior to use, check the product's condition and stop using immediately if you notice any deterioration from age/use, damage or irregularities.
- Please follow recommended care and storage instructions. Improper care and storage can lead to decrease in performance.
- Check the rope for signs of damage or if the knots have become loose. Old ropes or ropes that have been subjected to strong forces must be retired. Please purchase a new rope.

■ Prior to use, inspect this product for:

■Damage and loosening on the rope

Directions

- In order to maintain the strength of the rope, check and retie any knots that are loose.
- Make sure that there is at least 3cm of rope from the end of knots.

Bowline Knot

When tying someone or something to a rope.

- ○For making a loop on the end of a rope. ○Easy to tie, doesn't become loose. ○Easy to tie, easy to unite.
- and is strong.
- Easy to tie, easy to unite.



When tving something very tightly.


Clove Hitch

- The loop won't change dimensions A wide variety of uses in times of Ties together ropes with the same emergency.

Reef Knot

When tving two different, same thickness ropes together.

- thickness and made with the same material.





Double Fisherman's Knot

When tying something very tightly.


- OVery strong.
- OTving is difficult, untying is difficult.



Figure Eight Knot

When trying two different, same thickness ropes together.

OCreates a larger size knot than an overhand knot. OComparatively easy to untie.



Improper care and storage can shorten the lifespan of this product. Follow the recommendations below to extend the lifespan of your product.

- After use, rinse the product with fresh water to remove any sand or other debris and shade dry.
- OFor heavy soiling, wash with lukewarm water and a mild soap and rinse thoroughly.

Storage

- OStore in a well ventilated, cool, dry place out of direct sunlight.
- To prevent deforming and damage, do NOT store near heat sources.

Disposal

OPlease follow local regulations regarding waste disposal.

■ Warranty

Montbell's warranty covers all defects in materials and workmanship to the original owner, for the lifetime of the product. If a product ever fails due to a manufacturing defect, Montbell will repair or replace the product at its discretion. This warranty does not cover damage(s) caused by accident, improper care, negligence, misuse, alterations or normal wear and tear, Damage(s) not covered under warranty will be repaired at a reasonable rate. If you would like to make a warranty inquiry, please contact Montbell Customer Service or the store of original purchase.

■ Specifications

Name: Emergency Rope Size: φ 6mm Length: 7m Weight: 27g/m

All product specifications and design are subject to change without prior notice. Actual product specifications may vary.

mont-bell Co..Ltd.

2-2-2 Shinmachi, Nishi-ku, Osaka 550-0013 JAPAN www.montbell.com